# **BR1 Pro 5G**

## The Classic Goes Sonic



#### Sonic for a Reason

The 'classic goes sonic', why? The BR1 Pro 5G is integrated with the new generation multi-core CPU ensuring delivery of gigabit speeds. Achieving 800% faster speeds than the original BR1 Classic.

#### Upgrade to Wi-Fi 6

Experience less interference and connect to multiple devices simultaneously.

#### **Deploy with Confidence**


Just like the original BR1 Classic, the BR1 Pro 5G has also been certified to meet the standards of a wide array of deployment criterias.



### Low-Profile Form Factor

At 1.14 inches short, the BR1 Pro 5G is 25% slimmer than the BR1 Classic.







#### Available with PrimeCare

The economical way to build your secure SpeedFusion network. Experience it all with PrimeCare.

# MAX BR1 Pro 5G





# **Specifications**

WAN Interface	1x 10/100/1000/2500 Ethernet 1x Embedded Cellular Modem with Redundant SIM Slots	Antenna Connectors	4x SMA Cellular Connectors 2x RP-SMA Wi-Fi Antenna Connectors 1x SMA GPS Antenna Connector
LAN Interface	2x 10/100/1000M Ethernet	Power Input	10V – 30V DC
Wi-Fi Interface	Simultaneous Dual-Band (2.4GHz / 5GHz) Wi-Fi 6 2x2 MU-MIMO	Power Consumption	8W (nominal), 19W (max.)
	Wi-Fi WAN and/or AP	Dimensions	5.78 x 5.08 x 1.15 inches / 146.8 x 129 x 29.3 mm
SpeedFusion Features	Hot Failover, WAN Smoothing,	Weight	1.5 pounds / 680 grams
Nl (DVDV	Bandwidth Bonding <sup>1</sup>	Operating Temperature	-40° – 149°F / -40° – 65°C
Number of PepVPN SpeedFusion Peers	2/5 <sup>2</sup>	Humidity	15% – 95% (non-condensing)
Features	GPIO, Ignition Sensing	Certifications	FCC, CE, RoHS,
Router Throughput	1Gbps		E-Mark EN61373 Shock and Vibration Resistance EN50155 Railway Applications
SpeedFusion Throughput (No Encryption)	400 Mbps		Electronic Equipment used on Rolling Stock EN61000 Electromagnetic Compatibility
SpeedFusion Throughput (256-bit AES)	200 Mbps	Package Content	1x BR1 Pro 5G 4x LTE/5G Antennas (ACW-235) 2x Dual Band Wi-Fi Antennas (ACW-341)
Recommended Users	1-150		1x GPS Active Antenna (ACW-232) 1x 12V 2A 4 Pin Power Supply (ACW-632)
Cellular Data Rate <sup>3</sup>	5G: 4 Gbps / 700 Mbps		17 12 v 27 7 1 1111 owel Supply (Activ 032)
(Downlink / Uplink)	CAT-20: 2 Gbps / 150 Mbps	SIM Card Size	Nano-SIM (4FF)
		Warranty	1-Year Limited Warranty

Specifications are subject to change without notice.

<sup>&</sup>lt;sup>1</sup> Requires a PrimeCare subscription, complimentary for the first year. <sup>2</sup> 5 PepVPN Peers are enabled for PrimeCare models which requires a PrimeCare subscription, complimentary for the first year. <sup>3</sup> Maximum theoretical data rates.

# **MAX BR1 Pro 5G**



### **Ordering Information**

**Product Code** 

MAX-BR1-PRO-5GD-T-PRM Embedded Modem(s):

1x 5G

Regions

Primary: APAC, EMEA Compatibility: Global

**5G Bands** 

5G (NSA) Sub 6Ghz:

n1, n2, n3, n5, n7, n8, n12, n20, n28, n38, n41, n66, n71, n77, n78,

n79

**LTE Bands** 

B1, B2, B3, B4, B5, B7, B8, B12, B13, B14, B17, B18, B19, B20, B25, B26, B28, B29, B30, B32, B34, B38, B39,

B40, B41, B42, B46, B48, B66, B71

MAX-BR1-PRO-5GH-T-PRM

Embedded Modem(s): **1x 5G** 

Primary: North America\* Compatibility: Global

US Carrier Certifications: AT&T, T-Mobile, US Cellular, Verizon, FirstNet 5G (NSA) Sub 6Ghz:

n1, n2, n3, n5, n28, n41, n66, n71, n77, n78, n79

B1, B2, B3, B4, B5, B7, B8, B12, B13, B14, B17, B18, B19, B20, B25, B26, B28, B29, B30, B32, B34, B38, B39, B40, B41, B42, B46, B48, B66, B71

#### **Featured Add-ons**

Product Code

Description

PRM-MAX-BR1-PRO-5G-1Y 1-Year PrimeCare for BR1 Pro 5G

PRM-MAX-BR1-PRO-5G-2Y 2-Year PrimeCare for BR1 Pro 5G

PRM-MAX-BR1-PRO-5G-4Y 4-Year PrimeCare for BR1 Pro 5G

ACW-634 10ft DC Power Cable

ACW-643 Vehicle Cigarette to Molex Power Cable

ANT-MB-42G-S-B-6 7-in-1 Cellular and Wi-Fi Antenna System with GPS Receiver (Black)

ANT-MB-42G-S-W-6 7-in-1 Cellular and Wi-Fi Antenna System with GPS Receiver (White)